

Table of Contents

<u>WIC-1DSU-T1 WAN Interface Card Cable Specifications</u>	1
<u>Document ID: 46795</u>	1
<u>Introduction</u>	1
<u>Prerequisites</u>	1
<u>Requirements</u>	1
<u>Components Used</u>	1
<u>Conventions</u>	1
<u>WIC-1DSU-T1 WAN Interface Card</u>	1
<u>Cables</u>	2
<u>LEDs</u>	2
<u>Related Information</u>	3

WIC-1DSU-T1 WAN Interface Card Cable Specifications

Document ID: 46795

Introduction

Prerequisites

- Requirements
- Components Used
- Conventions

WIC-1DSU-T1 WAN Interface Card

Cables

LEDs

Related Information

Introduction

This document provides the cable specifications for the WIC-1DSU-T1 WAN interface card.

Prerequisites

Requirements

There are no specific requirements for this document.

Components Used


This document is not restricted to specific software and hardware versions.

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. If your network is live, make sure that you understand the potential impact of any command.

Conventions

For more information on document conventions, see the Cisco Technical Tips Conventions.

WIC-1DSU-T1 WAN Interface Card



The Cisco T1 DSU/CSU WAN interface card is an integrated, fully managed Data Service Unit/Channel Service Unit (DSU/CSU) for T1 or fractional T1 service. It is supported on the Cisco 1600, 1720, 2600, and

3600 Series Routers, and it provides a cost-effective router-DSU/CSU combination with the following features:

- T1 or fractional T1 network interface
- N X 64 kbps or N X 56 kbps non-channelized data rates (N = 1 to 24)
- Standards-based, including ANSI T1.403 and AT&T Publication 62411

Cables

This card requires an RJ-45 to RJ-45 straight-through cable (provided by customer).

The following table provides the pinouts for T1/E1 trunk and digital voice ports (RJ-48).

Pin ¹	Signal
1	RX (input)
2	RX (input)
3	---
4	TX (output)
5	TX (output)
6	---
7	---
8	---

¹Any pin not referenced on a connector is not connected.

LEDs

The table below provides the specifications for the T1/FT1 LEDs and the loopback button.

LED Feature	Color	Description
LP	Yellow	Line or loopback state is detected or is manually set by the user.
	Off	Normal operation
AL	Red	No receive signal
	Yellow	Remote station has an alarm condition.
	Blue	The remote station is probably out of service. If the remote station is an IOS-based router, its interface may be shut down.
	Off	Normal operation
CD	Green	The internal DSU/CSU in the WAN interface card is communicating with

		another DSU/CSU. This LED is on during normal operation.
Loopback button	---	Push this button to put the WAN interface card into loopback mode. The service provider can send a signal to test the connection from your site to the central office switch. Push this button again to turn loopback mode off.

Related Information

- [Technical Support – Cisco Systems](#)

All contents are Copyright © 1992–2005 Cisco Systems, Inc. All rights reserved. Important Notices and Privacy Statement.

Updated: Jun 26, 2005

Document ID: 46795
